

Leistungskurs Informatik

ST. 2 →	0	1	2	3	4	5	6	7	8	9	A	B	C	D	E	F
ST. 1																
↓	NUL	SOH	STX	EXT	EOT	ENQ	ACK	BEL	BS	HT	LF	VT	FF	CR	So	SI
0	0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15
1	DLE	DC1	DC2	DC3	DC4	NAK	SYN	ETB	CAN	EH	SUB	ESC	FS	GS	RS	US
	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31
2	SPC	!	„	#	\$	%	&	'	(	)	*	+	,	-	.	/
	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47
3	0	1	2	3	4	5	6	7	8	9	:	;	<	=	>	?
	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63
4	@	A	B	C	D	E	F	G	H	I	J	K	L	M	N	O
	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79
5	P	Q	R	S	T	U	V	W	X	Y	Z	[	\	]	^	_
	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95
6	`	a	b	c	d	e	f	g	h	i	j	k	l	m	n	o
	96	97	98	99	100	101	102	103	104	105	106	107	108	109	110	111
7	p	q	r	s	t	u	v	w	x	y	z	{		}	~	Δ
	112	113	114	115	116	117	118	119	120	121	122	123	124	125	126	127

Erläuterungen (Alle Zeichen lassen sich über die Tastatur mit **ALT** – **Zifferntastatur** eingeben.)

0	NUL	null im amerikanischen Sinne	11	VT	vertical tab	22	SYN	synchronous idle
1	SOH	start of heading	12	FF	form feed	23	ETS	end of transmissionblock
2	STX	start of text	13	CR	carriage return	24	CAN	cancel
3	ETX	end of text	14	SO	shift out	25	EM	end of medium
4	EOT	end of transmission	15	SI	shift in	26	SUB	substitute
5	ENQ	enquiry	16	DLE	data link escape	27	ESC	
6	ACK	acknowledgement	17	DC1	device controls	28	FS	file separator
7	BEL	bell	18	DC2		29	GS	group separator
8	BS	backspace	19	DC3		30	RS	record separator
9	HT	horizontal tab	20	DC4		31	US	unit separator
10	LF	line feed	21	NAK	negative acknowledge			

ASCII - Zeichensatztafel